

Transmitters**Hand Transmitter ULTRA Commander (SK 1 - 4)**

- Proved a million times
- Excellent workmanship
- 1 to 4-channel versions
- Straightforward layout with keys in different colours for each channel
- Coding switch with gold-plated and self-cleaning contacts
- Large transmitter range
- Simple operation
- Easy battery change with separate battery compartment
- Quick code setting
- Battery display by LED (visible from outside)
- Brown attractive housing

**Radio hand transmitter "SK"**

The „SK“ family hand transmitters have proved their value for many years in widely different applications.

Top priority is given by us to quality, workmanship and reliability.

So that you may be assured of continued trouble-free operation of our products.

We use only high-grade components that have passed our exacting tests, including coding switches with self-cleaning gold-plated contacts.

The hand transmitters are available in 1 to 4 channel variants.

Typical applications include, but are not limited to, the activation of doors openers, control of display boards in sports facilities, operation of tankers, activation of church tower bells, control of security devices, operation of fountains, activation of emergency calls for old people, control of lighting, etc.

Technical data:

Power supply:	9 volt monobloc battery (6 AM 6 / IEC 6 LR 61)
Battery life:	about 3 years (alkaline)
Power consumption	
on standby:	0 µA
on activation:	about 25 mA
Transmitter range:	about 70 - 120 meters (depending on terrain)
Housing:	ABS (plastic)
Housing colour:	brown (status 7/98)
Frequency:	40 MHz (a range not as heavily crowded as in 433 Mhz band)
Ambient temperature	
Operation:	- 20 to + 55° C
Storage:	- 30 to + 60° C
Weight:	about 86 g (excluding battery)
Dimensions:	about L 90 x W 60 x H 22 mm
This product is admitted after the European standards EN300683 / EN 300220 and CE is certificated	
Order Number:	SK 1 (single-channel transmitter)
Order Number:	SK 2 (two-channel transmitter)
Order Number:	SK 3 (three-channel transmitter)
Order Number:	SK 4 (four-channel transmitter)